

Atlas Copco Generators

Designed to perform, built to last



QAS 25 (60 Hz)

With standard features that maximize safety and minimize environmental impact, the QAS 25 also features:

- Diesel power from the reliable Kubota engine
- Electrical power from a Leroy Somer LSA series alternator
- Atlas Copco QC1002 control system
- 29 hour run time at 75% load with integrated 30 gallon in-frame fuel tank

The QAS 25 line offers quieter operation, reduced emissions, and lower acquisition and operating costs.

www.atlascopco.com/portablepower

Sustainable Productivity



Technical Data

Model	QAS 25
Rated Standby Power	22 kW / 28 kVA
Rated Prime Power	20 kW / 25 kVA
Voltage Selections - (L-L) 3Ø	220V
Voltage Selections - (L-N) 1Ø	127V
Amperage Capacity @ 220 volts 3Ø	66
Sound Pressure Level @ 23 feet @ 75% load	65 dB(A)
Fuel Tank Capacity	30 gal.
Fuel Consumption @ 75% load	1.04 gal/hr
Fuel Autonomy @ 75% load	29 hr

Engine	Kubota
Model	V2403
Rated Speed	1800 rpm
Emission Compliance	EPA IT4
Rated Output	29.6 HP @ 1800 rpm
Coolant	Water / Glycol
Cylinders	4
Displacement	2.4 L
Engine Control	Electronic

Alternator	Leroy Somer
Model	UCI 274 C1
Degree Of Protection / Insulation Class	IP23 / H

Dimensions and Weight	
Dimensions Skid (L x W x H)	82.5 x 37.4 x 51 in.
Weight - Skid Wet	1,868 lbs

The information contained herein is general in nature and is not intended for specific construction, installation or application purposes.

Generator Features and Options Include	
Multi-Voltage Selector Switch	●
Remote Start / Stop	●
Digital Control System	●
110% Fluid Containment	●
Electronic Governor	●
Trailer Mount	○
Battery Charger	○
Coolant Heater	○
Ball Coupling	○
Spare Tire	○
Rear Stabilizer Jacks	○
Tool Box	○
External Fuel Connections	○

Option: ○ Standard: ●



Control Panel

A comprehensive instrument panel enables all key operating functions to be supervised without opening the canopy. Analog gauges provide at-a-glance monitoring. Protected by a tough transparent cover, the single panel provides easy start up and control of the generator. The panel also provides full system monitoring to ease operation.

Atlas Copco Construction Equipment
 3700 East 68th Avenue
 Commerce City, CO 80022 USA
 Phone: +1 (800) 227-9144;
 Fax: +1 (303) 288-8828
 www.atlascopco.us



Use only authorized parts. Warranty or Product Liability does not cover any damage or malfunction caused by the use of unauthorized parts.

www.atlascopco.com